

VE7HME

Ver 2.2

Surrey Emergency Program Amateur Radio Society Net

With Simplex check-in test

19:25

"The Surrey Emergency Program Amateur Radio Society weekly two-meter net will start in 5 minutes."

5 minute warning and optional signal report to ensure you are being heard.

19:30

"Is this frequency in use? <YOUR CALLSIGN>"

Check if the frequency is in use

"Nothing heard"

1

Calling the Surrey Emergency Program Amateur Radio Net.

Calling the Surrey Emergency Program Amateur Radio Net.

This is <YOUR CALLSIGN—USE PHONETICS>. I will be net control this evening.

My name is <YOUR NAME>, and I am located in <YOUR SURREY DISTRICT>.

For the duration of the net I will use the SEPAR call sign **VE7HME**.

Call net. Introduce Net Control Station.

2

During an emergency or disaster all SEPAR members are asked to check-in to this repeater.

If this repeater fails to respond, please monitor 146.550 simplex for instructions.

Reminder of emergency communications simplex frequency

3

Is there any emergency or priority traffic? Please call <YOUR CALLSIGN>.

Call for emergency or priority traffic.

4

1) LIST ALL EMERGENCY & PRIORITY TRAFFIC:

LOOP WITH: Is there any further emergency or priority traffic?

2) MANAGE EXCHANGE OF ALL LISTED EMERGENCY TRAFFIC

3) MANAGE EXCHANGE OF ALL LISTED PRIORITY TRAFFIC.

Handle any emergency or priority traffic.

5

Is there any further emergency or priority traffic?

Ensure no (further) emergency traffic is waiting.

6

Nothing heard.

After no (further) traffic is listed.

7

This net meets every Tuesday at 1930 local time on 147.360 + 600 kHz and a tone of 110.9.

The purposes of this net are to provide training and emergency communications information related to the operation of SEPAR. This is a directed net. All check-ins and traffic are under the direction of the Net Control Station, but emergency traffic may break the net at any time.

SEPAR Net Introduction

8

Are there any Net Liaison stations?

Call for stations liaising with other nets.

9

1) ACKNOWLEDGE CALLS FROM NET LIAISON STATIONS ONE AT A TIME.

LOOP WITH: Any further Net Liaison stations?

2) KEEP ASKING FOR MORE UNTIL THERE ARE NO MORE RESPONSES HEARD.

Nothing heard.

Identify all net liaison stations on frequency.

10

Do we have any stations with formal traffic, we will list your traffic when you are acknowledged.

Please call **VE7HME**.

Call for formal traffic.

11

1) LIST ALL FORMAL TRAFFIC FROM EACH STATION IN TURN.

LOOP WITH: Are there any further stations with formal traffic?

2) MANAGE EXCHANGE OF ALL LISTED FORMAL TRAFFIC

Handle any formal traffic.

12

Are there any further stations with formal traffic?

One final check for (further) formal traffic is waiting.

13

Nothing heard.

After no (further) traffic is listed.

14

Any SEPAR Bulletins or Reports?

Call for SEPAR Bulletins or Reports.

15

1) LIST ALL BULLETINS AND REPORTS FROM EACH STATION IN TURN.

LOOP WITH: Are there any further stations with SEPAR bulletins or reports?

2) MANAGE DELIVERY OF ALL LISTED BULLETINS AND REPORTS. AT THE END OF EACH BULLETIN OR REPORT, CALL FOR QUESTIONS ON THAT BULLETIN OR REPORT.

Manage delivery of any SEPAR Bulletins or Reports.

16

Any further SEPAR Bulletins or Reports?

Ensure no (further) SEPAR Bulletins or Reports are waiting.

Nothing heard.

After no (further) SEPAR Bulletins or Reports are listed.

17

SEPAR Simplex Bulletin:

Following the repeater check-in portion of the net we will pause to do a roll-call based check-in using simplex. Tonight the simplex frequency will be < SELECTED VHF or UHF FREQUENCY >. Please indicate during the repeater check-in if you want to be included in the simplex roll-call. On simplex, Net control will call each station on the roll and if no response is received will call for any relays. If you are able to copy a response from the station called, please relay that station and your call sign to net control. At approximately 19:50 local, Net control will return to this repeater to report the results and conclude the net.

Are there any questions regarding this report?

18

We will now take check-ins from the six districts of Surrey.

Please give your call and wait to be acknowledged. Also indicate if you want to be added to the list for the Simplex Check-in roll-call. If you need to leave the net, please ask to be excused.

We will take check-ins in the order of:

- a) City Centre/Whalley,
- b) Cloverdale,
- c) Fleetwood,
- d) Guildford,
- e) Newton,
- f) South Surrey
- g) Outside Surrey
- h) Echolink.

We now take check-ins from City Centre/ Whalley.

Begin the check-in portion of the net.

19

**1) ACKNOWLEDGE STATIONS ONE AT A TIME
LOOP WITH: *Any further stations from <DISTRICT>?***

2) WORK THROUGH ALL SURREY DISTRICTS>
Take check-ins from all districts in order.

20

We will now take check-ins from Outside Surrey.

Call for check-ins from outside Surrey.

21

**1) ACKNOWLEDGE STATIONS ONE AT A TIME
LOOP WITH: *Any further stations from Outside Surrey?***

Take check-ins from outside Surrey.

22

Nothing heard.

We will now take check-ins from stations using Echolink.

Call for check-ins from Echolink.

23

*<ACKNOWLEDGE STATIONS ONE AT A TIME
LOOP WITH: **Any further stations using Echolink?**
WAIT SEVERAL SECONDS AFTER INVITATION TO ECHOLINK STATIONS TO
ALLOW THEM TO RESPOND.>*
Take check-ins from stations using Echolink.

24

Nothing heard.
Any late or missed check-ins from any area?
Final call for late or missed check-ins from any area.

25

Nothing heard.
This is **VE7HME** closing the check-in portion of the net.
We will now proceed with a Roll-call check-in on Simplex
Please monitor <SELECTED VHF or UHF FREQUENCY> Simplex and respond when called or to
relay a response. We will resume this repeater net at 1950hrs local.
This is <YOUR CALLSIGN> as Net control switching now to <SELECTED VHF or UHF
FREQUENCY> simplex
End check-in portion of net. Begin the Simplex check-in portion of net.

26

*A Simplex check-in roll call is presented by Simplex Net Control, who logs all direct and relay
responses then announce a return to the SEPAR repeater by 1950 local time.*

27

This is <YOUR CALLSIGN> resuming the SEPAR net at 1950local.
From a roll-call of _____ we had _____ direct and _____ relay responses
Thank you to all that were able to participate.
Do we have any stations with comments or feedback? Please call now.
Return, Report, Comments and Feed-back

28

Before closing, are there any other stations that have anything further for the net?
Ensure no further business.

29

Nothing heard.

A reminder that during an emergency or disaster all SEPAR members are asked to check-in to this
repeater. If this repeater fails to respond, please monitor 146.550 simplex for instructions.

Thank you all for participating in the SEPAR Net. We thank the Surrey Amateur Radio Club for the use
of this repeater.

This is <YOUR CALLSIGN> closing the net and returning the frequency to its normal use. 73
Close Net.